



# Garro Entity Pro


## Clenergy EV Platform Onboarding Guide

- Download the **Garro Connect** app for your device.







1. Install and open the Garo Connect app on your device. Select New User and follow the registration process or log in if you have previously registered.




2. On the overview screen, select the menu in the top-right corner of the screen.




3. Select Installers Menu to proceed.




4. Enter the site address details as required into the relevant fields.




5. Set the coordinates by selecting the icon on the right-hand side of the screen and tick to acknowledge the disclaimer. Select **Create location** to proceed.




6. Select **Add new unit +** to proceed.




7. Enter the device name and select Add new unit.



8. Select the charger you wish to onboard to proceed.




9. Read the information regarding the internet/grouping and select I have understood.




10. Enter the relevant details into the Group name and Group/Charging station max current (A) fields. Select Next to proceed.

11



11. Select the required network type required for your installation then select Save and continue installation.

12




12. Select OK, continue installation to proceed.

13



13. Select Continue installation.


14



14. Configure the grid connection parameters as required for your installation. Select Grid connection tested OK, confirm settings and proceed when correctly configured.




15



15. Select Continue installation.

16




16. Select Read QR code on bracket.

17




17. Scan the QR code located on the bracket and select Complete to proceed.


18



18. Select Continue installation.




19. Fit the charge point to the bracket, power up the charge point and wait for the LED to display a solid green light. Select Next to proceed.



20. Select the required network type for your installation and select Next to proceed.


**Please note:** It is recommended that an ethernet/Wi-Fi connection is used initially to ensure a quicker firmware update and connection to the Clenergy EV platform.

21



21. Select Read QR code and scan the code on the front of the charge point. Select Next once the QR code has been successfully read and the GaróCU- and Password fields have been automatically populated.

22




22. When prompted, allow your device to connect to the charge point.

23




23. Select the network that the charger is to be connected to and enter the relevant credentials to join if prompted. Select Next to proceed.

24




24. Once the network connection has been successfully established, select Close to proceed.

25




25. Select Close connection and Complete.


26




26. Allow the network connection to stabilise for several minutes before proceeding. A successful connection will be indicated by the globe icon turning green.

27




27. Select the  icon in the top right-hand side of the screen to open the General settings menu.

28




28. Select About my device.

29



29. Select Version update available.

30




30. Select the firmware version to be updated (if available) and allow the upload to take complete. Please allow around 10 minutes for this process to complete. Once completed, return to the General settings menu.

Please note: If a 4G/SIM network is to be used, it is recommended that the Update firmware automatically option remains off to avoid potential issues during future updates caused by signal drop-off.




31




31. Select Advanced to proceed.

32




32. Scroll to the bottom of the Configuration menu and select Select from list.

33




33. Select Clenergy-EV from the CSMS list.

34




34. On the Configuration menu select Update changes and if prompted reboot the charger.

35




35. Return to the main menu and select Continue installation.

36



36. Test and verify the installation as required (refer to the installation manual if needed).  
Declare the unit as tested and installed and select Next.



37. Each section on the main menu should now be complete and the charge point will be pointed to the Clenergy EV platform.

**Please note:** Make any necessary changes to the **electrical/network configurations** by using the **general settings** menu and the relevant sections.